

### APPLICATIONS

Premium quality low profile troffer with an almost limitless range of applications. Ideal for all commercial and industrial buildings requiring general illumination with recessed configurations.

### FEATURES & BENEFITS

- ◆ Housing embossed for maximum rigidity. Rounded side flanges for safe handling.
- ◆ Louvered heat removal slots on the back of the housing remove heat and prevent dust from entering the unit from the plenum
- ◆ Four corner tie points for safety wire supports
- ◆ Same ends fit 2x2 and 2x4
- ◆ Door frame hinges on end from either side of housing
- ◆ Prismatic lenses and all types of louvers can be fitted to door frame
- ◆ Optional damper screws onto outside of housing; controls air flow volume



### SPECIFICATIONS

Housing: 3 3/4" deep. Die formed standard or 20 gauge steel. Ends snap into housing or can be secured with #8 x 3/8" screw or 1/8" pop rivet with 1/8" to 3/16" grip (not included). Access plate snaps in for easy access. Flush steel door frame. Air intake slots and baffles are built into the ends of the door frame. White polyester polymer finish with a minimum 82% reflectivity. Designed for recess installation in exposed T-bar ceilings. Designed for concealed Z-bar ceilings. Leveling lugs (4 included) attached to each corner of body for use with concealed Z-bar ceilings. Joiner connects and aligns ends of housing in continuous runs. It overlaps ends and is attached by bending tabs.

### ORDERING DATA

EXAMPLE: RGAIR22-214DMV125


RGAIR

Series	Size	# of Lamps	Ballast	Lens	Options
RGAIR	22 2x2	2	MV 120-277VAC	Blank A12 .100 thick lens	B1 T8/T5 1L 500 Lumens Battery Backup (B11)
LED Grid	24 2x4	3 4 per cross section	PMV Program Start	125 A12 .125 thick lens	B2 T8/T5 1L/2L 700 Lumens Battery Backup (B48)
			DMV Sylvania Powersense Dimming	CL Clear .100 thick lens	B3 T8/T5 1L/2L 1400 Lumens Battery Backup (B223)
			LED Less ballast wired one end hot*	CL125 Clear .125 thick lens	B51 T5HO 1L 500 Lumens Battery Backup (B625)
			LED2 Less ballast wired both ends hot*	SW Smooth White .100 thick lens	B52 T5HO 1L 800 Lumens Battery Backup (B585)
					B53 T5HO 1L 1300 Lumens Battery Backup (B626)
					EMK12 1200 Board Lumen LED Emergency Kit
					11 Dual Ballasts 1 Lamp + 1 Lamp
					21 Dual Ballasts 2 Lamp + 1 Lamp
					22 Dual Ballasts 2 Lamp + 2 Lamp
					31 Dual Ballasts 3 Lamp + 1 Lamp
					L35 735K Lamps Installed
					L41 741K Lamps Installed
					L841 841K Lamps Installed
					L835 835K Lamps Installed


\*Assembled with no ballast. Made for UL Listed, self ballasted retrofit T8 LED lamps.

Dimensions and specifications subject to change without notice.

**DIMENSIONS**



End View: RGAIR Economy Lay-in



End View: RGAIR Economy Flange Lay-in

Dimensions and specifications subject to change without notice.